GigaVUE Hardware Product Comparison Chart

| | COTS Switches | GigaVUE TA Series | | | GigaVUE HC Series | | | | |
|---------------------------------------|--------------------|------------------------|--------------------------|-------------------|-------------------|-----------------|----------------------|--------------------|--|
| Product (running GigaVUE-OS) | Dell S4112F-ON | GigaVUE- TA25/TA25E | GigaVUE- TA200/TA200E | GigaVUE- TA400 | GigaVUE- HCT | GigaVUE- HC1 | GigaVUE- HC1-Plus | GigaVUE- HC3 | |
| Physical Specifications | | | | | | | | | |
| Height (rack units) | 1RU | 1RU | 2RU | 1RU | 1RU | 1RU | 1RU | 3RU | |
| Width (19" rack) | Half | Full | Full | Full | Half | Full | Full | Full | |
| Modular Design | - | - | _ | - | ✓ | ✓ | ✓ | ✓ | |
| AC or DC Redundant Power Supply | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Field Replaceable Cooling Fans | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Throughput & Capacity | | | | | | | | | |
| Maximum Visibility ¹ | 840Gb | 2Tb | 6.4Tb | 12.8Tb | 500Gb | 604Gb | 1.8Tb | 6.4Tb | |
| Maximum Map Filter Rules ¹ | 8k | 18k ¹ | 24k1 | 88k | 3k | 16k | 36k | 24k | |
| Maximum Port Densities | | | | | | | | | |
| 10/100Mb Ports ¹ | - | - | - | - | 12 | 32 | - | - | |
| 1Gb Ports ¹ | 12 | 48 | - | - | 12 | 40 | 32 | - | |
| 10Gb Ports ¹ | 12/24 ² | 56/80 ² | 128 ² | 128 ² | 32 | 60 ² | 72 ² | 128 2 | |
| 25Gb ports | - | 56/80 ² | 128 ² | 128 ² | 12 | - | 72 ² | 128 ² | |
| 40Gb Ports ¹ | 3 | 8 | 64 | 32 | 6 | 8 | 12 | 64 | |
| 100Gb Ports ¹ | 3 | 8 | 64 | 128 ² | 2 | - | 12 | 32/64 ³ | |
| 400Gb Ports ¹ | _ | _ | - | 32 | - | _ | - | _ | |
| Port Transceiver Types | | | | | | | | | |
| 10/100/1000BASE-T Copper SFP | √ 5 | √ 5 | - | - | ✓ | ✓ | √ 5 | - | |
| 1Gb SFP | ✓ | ✓ | - | - | ✓ | ✓ | ✓ | - | |
| 10Gb SFP+ | ✓ | √ | - | - | ✓ | √ | √ | √ | |
| 25Gb SFP28 | - | ✓ | - | _ | ✓ | - | ✓ | √ 3 | |
| 40Gb QSFP+ | √ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| 100Gb QSFP28 | ✓ | ✓ | ✓ | ✓ | ✓ | - | √ | √ | |
| 400Gb QSFP-DD | - | - | _ | ✓ | - | - | _ | - | |

| | COTS Switches | GigaVUE TA Series | | | GigaVUE HC Series | | | | |
|---|-------------------|------------------------|--------------------------|-------------------|-------------------|-----------------|----------------------|-----------------|--|
| Product (running GigaVUE-OS) | Dell S4112F-ON | GigaVUE- TA25/TA25E | GigaVUE- TA200/TA200E | GigaVUE- TA400 | GigaVUE- HCT | GigaVUE- HC1 | GigaVUE- HC1-Plus | GigaVUE- HC3 | |
| Integrated Taps | | | | | | | | | |
| 10/100/1000Base-T Copper Tap | - | - | - | - | ✓ | ✓ | √ 5 | - | |
| 1Gb/10Gb Fiber Network Tap | - | - | - | - | _ | - | - | _ | |
| 10/100/1000Base-T Copper Bypass Tap | - | - | - | - | √ | ✓ | ✓ | - | |
| 1Gb Fiber Bypass Tap | - | _ | - | - | ✓ | ✓ | ✓ | - | |
| 10Gb Fiber Bypass Tap | _ | _ | _ | _ | ✓ | ✓ | ✓ | ✓ | |
| 40Gb Fiber Bypass Tap | - | _ | - | - | _ | _ | _ | ✓ | |
| 100Gb Fiber Bypass Tap | - | - | - | - | - | - | - | ✓ | |
| 400Gb Fiber Bypass Tap | - | - | - | - | - | - | - | - | |
| GigaSMART® Engines per Module | | | | | | | | | |
| Front Module | N/A | N/A | N/A | N/A | 1 | 1 | 1 | 2 | |
| Built-in or Rear Module | N/A | N/A | N/A | N/A | _ | 1 | 1 | - | |
| GigaVUE-OS Function & Features | | | | | | | | | |
| Flow Mapping® | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| VLAN Tagging | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Logical Inline Bypass Protection | - | ✓ | √ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| User-defined Attribute Filtering | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Traffic Aggregation & Replication | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Traffic Distribution (load-balancing) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Stacking Ports | √ 4 | √ 4 | √ 4 | √ 4 | ✓ | ✓ | ✓ | ✓ | |
| Configuration Log | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Role-Based Access Control (RBAC) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |
| Port Access Control—Multiple Level | ✓ | ✓ | ✓ | ✓ | √ | ✓ | ✓ | ✓ | |
| CLI Configuration and Management | ✓ | ✓ | ✓ | ✓ | √ | ✓ | ✓ | ✓ | |
| REST API Configuration and Management (via FM) | ✓ | ✓ | √ | ✓ | √ | V | V | ✓ | |
| GUI Configuration and Management | ✓ | ✓ | ✓ | ✓ | √ | √ | ✓ | ✓ | |
| Configuration from GigaVUE-FM | ✓ | ✓ | ✓ | ✓ | √ | √ | ✓ | ✓ | |
| Ansible Automation with GigaVUE-FM | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | |

| | COTS Switches | COTS Switches GigaVUE TA Series | | | GigaVUE HC Series | | | | |
|---|-------------------|---------------------------------|--------------------------|-------------------|-------------------|-----------------|----------------------|-----------------|--|
| Product (running GigaVUE-OS) | Dell S4112F-ON | GigaVUE- TA25/TA25E | GigaVUE- TA200/TA200E | GigaVUE- TA400 | GigaVUE- HCT | GigaVUE- HC1 | GigaVUE- HC1-Plus | GigaVUE- HC3 | |
| SNMP v1/v2/v3 Support | ✓ | ✓ | ✓ | √ | ✓ | √ | ~ | ✓ | |
| Remote Access via Telnet or SSH2 | ✓ | ✓ | ✓ | √ | ✓ | ✓ | ✓ | ✓ | |
| Remote Authentication (RADIUS, TACACS+) | ✓ | ✓ | ✓ | ✓ | √ | ✓ | ✓ | √ | |
| Header Stripping (MPLS, VLAN, VxLAN) | _ | √ 4 | √ 4 | √ 4 | ✓ | ✓ | ✓ | ✓ | |
| Tunneling (L2GRE, VxLAN) | √ 4 | √ 4 | √ 4 | √ 4 | ✓ | ✓ | ✓ | ✓ | |
| MAC Address Rewrite | - | √ 4 | √ 4 | √ 4 | ✓ | ✓ | ✓ | ✓ | |
| Time Stamping | - | _ | √ 4 | - | - | _ | - | _ | |
| NEBS Level 3 Certified | - | _ | √ 7 | √ | ✓ | ✓ | ✓ | ✓ | |
| GigaSMART® Applications & Features | | | | | | | | | |
| Traffic Intelligence | | | | | | | | | |
| Source Port Labeling | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Advanced Header Stripping | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| De-duplication | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Packet Slicing | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Advanced Flow Slicing | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Masking | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Adaptive Packet Filtering | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Advanced Load-Balancing | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Advanced Tunneling (Including ERSPAN Termination and TCP Tunneling) | N/A | N/A | N/A | N/A | √ | √ | V | ✓ | |
| NetFlow Generation | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Application Intelligence | | | | | | | | | |
| Application Filtering Intelligence | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Application Metadata Intelligence | N/A | N/A | N/A | N/A | √ | ✓ | ✓ | √ | |

© 2023-2025 Gigamon. All rights reserved.

| | COTS Switches | GigaVUE TA Series | | | GigaVUE HC Series | | | | |
|--|-------------------|------------------------|--------------------------|-------------------|-------------------|-----------------|----------------------|-----------------|--|
| Product (running GigaVUE-OS) | Dell S4112F-ON | GigaVUE- TA25/TA25E | GigaVUE- TA200/TA200E | GigaVUE- TA400 | GigaVUE- HCT | GigaVUE- HC1 | GigaVUE- HC1-Plus | GigaVUE- HC3 | |
| Application Visualization | N/A | N/A | N/A | N/A | ✓ | ✓ | ✓ | ✓ | |
| Subscriber Intelligence | | | | | | | | | |
| 5G Correlation | N/A | N/A | N/A | N/A | - | - | - | ✓ | |
| GTP Correlation | N/A | N/A | N/A | N/A | - | - | ✓ | ✓ | |
| Security Intelligence | | | | | | | | | |
| TLS/SSL Decryption (Inline and Out-of-Band) | N/A | N/A | N/A | N/A | √ 6 | ✓ | ✓ | ✓ | |

Support and Services

Gigamon offers a range of support and maintenance services For details regarding Gigamon Limited Warranty and its Product Support and Software Maintenance Programs, visit **gigamon.com/support-and-services/overview-and-benefits**.

Gigamon®

Worldwide Headquarters

3300 Olcott Street, Santa Clara, CA 95054 USA +1 (408) 831-4000 | gigamon.com

© 2023-2025 Gigamon. All rights reserved. Gigamon and Gigamon logos are trademarks of Gigamon in the United States and/or other countries. Gigamon trademarks can be found at gigamon.com/legal-trademarks. All other trademarks are the trademarks of their respective owners. Gigamon reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

¹ Dependent on configured modules

² Using breakout, such as G-TAP PNL-M341

³ Requires GigaVUE-HC3 Control Card Version 2

⁴ With Advanced Features License

^{5 1000}Mbps only

⁶ Only Out-of-band is Supported

⁷ Only TA200